



## Merrychef eikon® e2s

Ideal for cafés, bars, convenience stores and quick service outlets



Microwave



Convection



Tuned impingement

The Merrychef **eikon® e2s** is the most versatile high speed oven on the market with a ground breaking cavity (12"x12") to oven width (14") ratio to maximise use of space. The high power model boasts queue busting speeds up to 20x faster than a conventional oven and the standard power up to 12x faster. Designed for front of house, the eikon® e2s is available in a Classic stainless steel or Trend red and black with accessory storage on top of the unit. Quietly operating at 45.3dba in standby mode.

### eikon® e2s Classic/eikon® e2s Trend

Colours

**eikon® e2s Classic:** Stainless steel **eikon® e2s Trend:** Red Black

Dimensions (external) W x D x H

**eikon® e2s Classic:** 356 x 595 x 620 mm *(depth excludes handles)*

**eikon® e2s Trend:** 356 x 595 x 644 mm *(depth excludes handles)*

Dimensions (internal) W x D x H

311 x 311 mm / 12¼" x 12¼"

Can be stacked

Using a high speed oven stacking trolley

Model	Part number	Convection/ Microwave	Electrical Supply* Max.Power Input	Plug type
<b>eikon® e2s Classic</b> Standard Power	e25GXMV5AAU2CLUK	2200 W/1000 W	220-230 V/50 Hz 3680 W	13A Single Phase socket
<b>eikon® e2s Classic</b> High Power	e25DBMV5HEU2CLEU	2200 W/2000 W	220-230 V/50 Hz 6000 W	32A Single Phase socket
<b>eikon® e2s Classic</b> High Power	e25DBMV5GCU2CLEU	2200 W/2000 W	220-230 V/50 Hz 2500 W + 3000 W	16A/32A Three Phase socket
<b>eikon® e2s Trend</b> Standard Power	<b>Black:</b> e25GXMV5AAU2BKLUK <b>Red:</b> e25GXMV5AAU2RDUK	2200 W/1000 W	220-230 V/50 Hz 2990 W	13A Single Phase socket
<b>eikon® e2s Trend</b> High Power	<b>Black:</b> e25DBMV5HEU2BKEU <b>Red:</b> e25DBMV5HEU2RDEU	2200 W/2000 W	220-230 V/50 Hz 6000 W	32A Single Phase socket
<b>eikon® e2s Trend</b> High Power	<b>Black:</b> e25DBMV5GCU2BKEU <b>Red:</b> e25DBMV5HEU2RDEU	2200 W/2000 W	220-230 V/50 Hz 2500 W + 3000 W	16A/32A Three Phase socket

\* Custom voltages and plug types available on request

#### Circuit Breakers for Merrychef Ovens

Model	Recommended Circuit	Breaker (per phase)	Alternative Recommended
<b>eikon® e2s Classic</b>	Standard Power	C20	D16
<b>eikon® e2s Classic</b>	High Power	C40	D32